

ECODESIGN INFORMATION

Applies to non-residential ventilation units (NRVU)

According to Regulation EU No 1253/2014 of the European Commission, implementing Directive 2009/125/CE of European Parliament

SODECA, S.L.U.

www.sodeca.com

b) Model
c) Typology
d) Drive type
e) HRS type
f) Thermal efficiency of heat recovery (%)
g) Nominal flowrate
h) Effective electric power input
i) SFPint
j) Face velocity at design flow rate
k) Nominal external pressure
l) Internal pressure drop of ventilation components
m) Internal pressure drop of non-ventilation components
n) Static efficiency of fans according to (EU) 327/2011
o1) Max. internal leakage rate
o2) Max. external leakage rate
p) Energy performance of the filters
q) Visual filter warning
r) LWA radiated

b)	c)	d)	e)	f)	g)	h)	i)	j)	k)	l)	m)	n)	o1)	o2)	p)	q)	r)	ERP
				%	m³/s	kW	Wm³/s	m/s	Pa	Pa	Pa	%	%	%			dBA	
SV/FILTER-125 G4+F6	NRVU / UVU	Zmienna prędkość	Nic		0.047	0.111	230	4.70	300	32		53.6	2.5		G4: G; F6: F	Zobacz instrukcję	41	2018
SV/FILTER-150 G4+F6	NRVU / UVU	Zmienna prędkość	Nic		0.074	0.156	230	3.70	372	46		60.4	2.5		G4: G; F6: F	Zobacz instrukcję	52	2018
SV/FILTER-200 G4+F6	NRVU / UVU	Zmienna prędkość	Nic		0.110	0.093	230	3.67	130	49		59.1	2.5		G4: G; F6: F	Zobacz instrukcję	56	2018
SV/FILTER-250 G4+F6	NRVU / UVU	Zmienna prędkość	Nic		0.122	0.189	230	2.44	345	60		60.4	2.5		G4: G; F6: F	Zobacz instrukcję	60	2018
SV/FILTER-315 G4+F6	NRVU / UVU	Zmienna prędkość	Nic		0.282	0.122	230	3.53	70	79		64.7	2.5		G4: G; F6: F	Zobacz instrukcję	62	2018
SV/FILTER-350 G4+F6	NRVU / UVU	Zmienna prędkość	Nic		0.400	0.202	230	4.00	126	106		64.7	2.5		G4: G; F6: F	Zobacz instrukcję	65	2018
SV/FILTER-400 G4+F6	NRVU / UVU	Zmienna prędkość	Nic		0.449	0.398	230	3.45	257	90		68.5	2.5		G4: G; F6: F	Zobacz instrukcję	67	2018
SV/FILTER-125 F6+F8	NRVU / UVU	Zmienna prędkość	Nic		0.052	0.114	230	5.20	280	33		53.6	2.2		F6: F; F8: A	Zobacz instrukcję	41	2018
SV/FILTER-150 F6+F8	NRVU / UVU	Zmienna prędkość	Nic		0.082	0.161	230	4.10	345	46		60.4	2.2		F6: F; F8: A	Zobacz instrukcję	52	2018
SV/FILTER-200 F6+F8	NRVU / UVU	Zmienna prędkość	Nic		0.122	0.095	230	4.07	117	49		59.1	2.2		F6: F; F8: A	Zobacz instrukcję	56	2018
SV/FILTER-250 F6+F8	NRVU / UVU	Zmienna prędkość	Nic		0.134	0.192	230	2.68	312	59		60.4	2.2		F6: F; F8: A	Zobacz instrukcję	60	2018
SV/FILTER-315 F6+F8	NRVU / UVU	Zmienna prędkość	Nic		0.305	0.124	230	3.81	58	76		64.7	2.2		F6: F; F8: A	Zobacz instrukcję	62	2018
SV/FILTER-350 F6+F8	NRVU / UVU	Zmienna prędkość	Nic		0.436	0.204	230	4.36	106	102		64.7	2.2		F6: F; F8: A	Zobacz instrukcję	65	2018
SV/FILTER-400 F6+F8	NRVU / UVU	Zmienna prędkość	Nic		0.489	0.405	230	3.76	227	87		68.5	2.2		F6: F; F8: A	Zobacz instrukcję	67	2018
SV/FILTER-125 F7+F9	NRVU / UVU	Zmienna prędkość	Nic		0.049	0.113	230	4.90	291	33		53.6	2.1		F7: A; F9: A	Zobacz instrukcję	41	2018
SV/FILTER-150 F7+F9	NRVU / UVU	Zmienna prędkość	Nic		0.078	0.158	230	3.90	359	46		60.4	2.1		F7: A; F9: A	Zobacz instrukcję	52	2018
SV/FILTER-200 F7+F9	NRVU / UVU	Zmienna prędkość	Nic		0.115	0.094	230	3.83	124	49		59.1	2.1		F7: A; F9: A	Zobacz instrukcję	56	2018
SV/FILTER-250 F7+F9	NRVU / UVU	Zmienna prędkość	Nic		0.127	0.190	230	2.54	329	60		60.4	2.1		F7: A; F9: A	Zobacz instrukcję	60	2018
SV/FILTER-315 F7+F9	NRVU / UVU	Zmienna prędkość	Nic		0.293	0.123	230	3.66	64	77		64.7	2.1		F7: A; F9: A	Zobacz instrukcję	62	2018
SV/FILTER-350 F7+F9	NRVU / UVU	Zmienna prędkość	Nic		0.417	0.203	230	4.17	116	104		64.7	2.1		F7: A; F9: A	Zobacz instrukcję	65	2018
SV/FILTER-400 F7+F9	NRVU / UVU	Zmienna prędkość	Nic		0.468	0.402	230	3.60	242	89		68.5	2.1		F7: A; F9: A	Zobacz instrukcję	67	2018